



FAST RECOVERY
GLASS PASSIVATED BRIDGE RECTIFIER
Reverse Voltage:600Volts
Forward Current:20.0 Amps

### **FEATURES**


- Plastic package has Underwriters Laboratory Flammability Classification 94V-0
- · Glass passivated chip junction
- · High current capability.Low forward voltage drop
- · Soft recovery improves EMC performance
- · High temperature soldering guaranteed:260°C/10 seconds at terminals
- · Component in accordance to RoHS 2015/863/EU

### MECHANICAL DATA

- · Case: GBU molded plastic body
- Terminals: Plated leads solderable per MIL-STD-750,method 2026
- · Mounting Position: Any

## TYPICAL APPLICATIONS

Used in AC/DC bridge full wave rectification for SMPS, lighting ballaster, adapter, charger, home appliances, office equipment, and telecommunication applications.



Dimensions in inches and (millimeters)

## MAXIMUM RATINGS AND ELECTRICAL CHARACTERISTICS

(Rating at 25°C ambient temperature unless otherwise specified. Single phase ,half wave , resistive or inductive load. For capacitive load,derate current by 20%.)

Parameters		Symbol	RGBU2006	Units
Maximum Reverse Peak Reverse Voltage		$V_{RRM}$	600	Volts
Maximum RMS Voltage		$V_{\text{RMS}}$	420	Volts
Maximum DC Blocking Voltage		$V_{DC}$	600	Volts
Maximum Average Forward Rectified Current, (See Fig 2)		I <sub>F(AV)</sub>	20.0	Amps
Peak Forward Surge Current 8.3ms single half sine-wave superimposed on rated load		I <sub>FSM</sub>	300	Amps
Rating for Fusing (t =8.3ms)		l²t	373	A <sup>2</sup> S
Maximum Instantaneous Forward Voltage at 10.0A DC		V <sub>F</sub>	1.15	Volts
Maximum DC Reverse Current at rated DC blocking voltage	T <sub>A</sub> =25°C	I <sub>R</sub>	5	μΑ
	T <sub>A</sub> =125℃		100	μΑ
Typical Junction Capacitance (Note 1)		C,	70	pF
Typical thermal resistance (Note 2)  Junction-Ambient Junction-Case		$\begin{array}{c} R_{_{\theta JA}} \\ R_{_{\theta JC}} \end{array}$	25 1.5	°C/W
Maximum reverse recovery time(Note3)		trr	500	ns
Operating junction and storage temperature range		Tu Tstg	-55 to +150	°C


NOTE: 1.Measured at 1MHz and applied reverse voltage of 4.0 Volts.


2 Unit mounted on 50mm x 50mm x 1.6mm copper plate heatsink


3.Test conditions:  $I_F = 0.5A$ ,  $I_R = 1.0A$ ,  $I_{RR} = 0.25A$ .


REV: OCT-2022













# Friendship Reminder

- JiNan JingHeng (hereinafter referred to as JH) reserves the right to make changes to this document and its products and specifications at anytime without notice.
- Customers should obtain and confirm the latest product information and specifications before final design, purchase or use.
- JH makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does JH assume any liability for application assistance or customer product design.
- JH does not warrant or accept any liability with products which are purchased or used for any unintended or unauthorized application.
- No license is granted by implication or otherwise under any intellectual property rights of JH.
- JH's products are not authorized for use as critical components in life support devices or systems without express written approval of JH.